

Generatoare de curent 400V



Echipamente
fabricate
in Franta

Tristar 12500 XL21 DE

Powered by:



SUBARU

Robin Industrial Products



Echipare standard:

- Racire cu aer (filtru inclus)
- Senzor lipsa ulei (ce opreste functionarea motorului)
- 2 prize 220V / 50Hz Ip44 10/16A Schuko
- Protectie prize cu disjuncteur termic
- Pornire manuala la sfoara
- Cadru ranforsat cu diam. 30 mm

Seria Tristar	12500 XL21 DE
Putere maxima 400V	15 kVA
	12 kW
Putere maxima 230V	3.6 kW
In regim continuu 400V	10 kW
Amperaj 400V	21.7 A
Amperaj 230V	15.6 A
Frecventa	50 Hz
Tip motor	Subaru EH 65
Combustibil	Benzina
Capacitate rezervor	21 l
Autonomie	5 h 30 min.
Zgomot (la 7m)	79 dB(A)
Putere sonora	104 Lwa
Greutate	120 kg
Dimensiuni LxIxh (mm)	935x575x575

**Concepute pentru utilizare
intensa in santiere**

Echipare optionala:

- Varianta XL = rezervor marit
- Varianta DE = demaraj electric
- Varianta N/S = pornire automata
- Regulator de tensiune electronica AVR
- Pornire la cheie
- Pornire automatizata
- Kit diferential 30 mA + priza impamantare
- Kit roti
- Kit intretinere (filtre + ulei)

Servicii incluse:



Distribuitor local